




Bernd Karle Hard- und Softwareentwicklung  
Blauenweg 6  
79379 Müllheim, Germany  
Phone: +49 (0)7631-172375  
E-Mail: [info@bksoft.de](mailto:info@bksoft.de)  
Web: <http://www.bksoft.de> / <http://www.casino-software.de>

## bill to coin validator adapter v1.01




Occupation of the 10 pole plug (NRI G13 compatible):



Pin 1 = -V (GND)	Pin 6 = Total blocking
Pin 2 = +V (+12V DC)	Pin 7 = Output line 1
Pin 3 = Output line 5	Pin 8 = Output line 2
Pin 4 = Output line 6	Pin 9 = Output line 3
Pin 5 = Return	Pin 10 = Output line 4

Occupation of the 16 pole plug (NV 10 compatible):



Pin 1 = +V (+12V DC)	Pin 9 = Inhibit 1
Pin 2 = -V (GND)	Pin 10 = Inhibit 2
Pin 3 = MDB	Pin 11 = Inhibit 3
Pin 4 = MDB	Pin 12 = Inhibit 4
Pin 5 = MDB	Pin 13 = Output line 3
Pin 6 = MDB	Pin 14 = Output line 4
Pin 7 = Busy	Pin 15 = Output line 1
Pin 8 = Escrow	Pin 16 = Output line 2

JP1-1 bill signal to coin output line 1  
JP1-2 bill signal to coin output line 2  
JP1-3 bill signal to coin output line 3  
JP1-4 bill signal to coin output line 4  
JP1-5 bill signal to coin output line 5  
JP1-6 bill signal to coin output line 6  
JP1-7 bill power supply via coin  
JP1-8 bill power supply via X4  
JP1-9 bill inhibit

X4-1: +12V DC  
X4-2: GND